

ABSTRACT

A possible system realization of a high quality (Q) factor bandpass filter is proposed. Two circuit realizations through Techniques 1 and 2 of fully balanced, high-Q, wide-dynamic-range current-tunable Gm-C bandpass filters are presented. Technique 1 is relatively simple based on two fully balanced components, i.e. a two-input adder and a low-Q-based bandpass filter. The high quality Q_{HQ1} factor of Technique 1 is approximately equal to a typically high (> 100) and constant value of a common-emitter current gain (β) and is, for the first time, independent of variables such as a center frequency. Possible solutions for good stability of Q_{HQ1} with temperature are suggested through the use of Heterojunction Bipolar Transistors (HBTs) where the β is relatively constant. Not only can the need for additional Q-tunable circuits be greatly reduced, the sensitivity of the Q factor can be greatly improved.

Sensitivities of either the Q factor or the center frequency to the variation of parameters in Technique 1 are constant between 1 to -1 and are no longer strongly affected by the Q factor or variables. As a simple example at 10.7 MHz, Technique 1 demonstrates the high quality factor Q_{HQ1} factor of 121, the low total output noise of $5.303 \mu V_{rms}$, the 3rd-order intermodulation-free dynamic range (IMFDR₃) of 74.45 dB and the wide dynamic range of 87.45 dB at 1% IM₃. The upper limit of Q_{HQ1} is expected at approximately 160 at a maximum β of 190. The upper limit of center frequency is expected at approximately 600 MHz at a capacitance of 1 pF. The center frequency is current tunable over 3 orders of magnitude. The temperature coefficient of normalized center frequency is approximately $-30 \text{ ppm}/^\circ\text{C}$.

Technique 2 is also relatively simple based on three fully balanced components, i.e. a two-input adder, a low-Q-based bandpass filter and a differential amplifier. The high quality factor Q_{HQ2} of Technique 2 is possible through a tunable bias current. As a simple example at 10.7 MHz, the paper demonstrates the quality factor Q_{HQ2} of 223, the low total output noise of $2.559 \mu V_{rms}$, the 3rd-order intermodulation-free dynamic range (IMFDR₃) of 80.82 dB, and the wide dynamic range of 101.02 dB at 1% IM₃. The centre frequency is current tunable over 3 orders of magnitude. For very high Q realizations, the sensitivities of the Q factor to the variation of parameters in Technique 2 are in the same order as other existing approaches whilst the sensitivities of center frequency to the variations of parameter are constant values from -1 to 1. The upper limit of center frequency is expected at approximately 500 MHz at a capacitance of 1 pF. The center frequency is current tunable over 3 orders of magnitude. The temperature coefficient of normalized center frequency is approximately -30 ppm/°C. Comparisons of Techniques 1 and 2 to other 10.7-MHz Gm-C approaches are also included. The two proposed 10.7-MHz techniques described in Techniques 1 and 2 offer the high-Q wide-dynamic-range current-tunable Gm-C bandpass filter.